

SecuMaster

SMF-670 & SMF-870

SMF-670

SMF-870



- Time and Attendance
- Site Security and Access Control

WEB BASED FINGERPRINT SYSTEM

SMF-670 & SMF-870 Fingerprint System

FEATURES

- ⊗ Double Badge Control
- ⊗ Dual Door Interlocking
- ⊗ On-line Viewing Door status via Web Browser
- ⊗ Audible indicators
- ⊗ Optical-based technology (SMF-670)
- ⊗ With Master / Slave function
- ⊗ Support 100 holidays
- ⊗ Support 255 time sets, 255 time zones, 200 groups
- ⊗ Support 128 department, 128 designations
- ⊗ LCD on-screen menus, simple enrollment process
- ⊗ Low power consumption, low cost of system maintenance
- ⊗ Use of stand-alone mode or working in conjunction with Ethernet/Internet
- ⊗ **Build in http server, can use web browser to make system management**
- ⊗ Support 40 sets, function key setting
- ⊗ Elevator control up to 9 lifts, 128 floors/lift (need SF-333)
- ⊗ Multi-door control up to 8 doors (16 external readers & need SF-20)
- ⊗ Selectable time zone for FP + Pin/Card + Pin/Lock Release/Exit Button
- ⊗ Anti Pass Back (No Tolerance/Period Timer), Offline with Un-limited Level, No Need Online Software Support



SPECIFICATIONS

	670	870
Verification Method	Fingerprint, RFID + Fingerprint, Fingerprint + Password, RFID + Fingerprint + Password	RFID, RFID + Password, Password
Verification Mode	1 : 1 (4.500 persons), 1 : N (Less than 1000 persons)	
Verification Time	Less than 2.0 sec	Less than 1.0 sec
Registration Time	Less than 3.0 sec	
False Rejection Rate (FRR)	Less than 0.01%	
False Acceptance Rate (FAR)	Less than 0.001%	
Capacity	4.500 persons (9.000 templates)	5.000 users (extendable 10.000/20.000/50.000)
Power	DC 9-30V 1A	
Communication	RS-/485 : External Reader & Relay Box RS-232 : Dial up Modem or Mini Printer TCP/IP, Weigand 26/34 Input & Output	
Communication Speed	38400/19200/9600 BPS ; TCP/IP : 10/100M, Auto Crossing	
RFID Function	125 Khz (EM/TM), 13,56 Mhz (Mifare)	
Log Data	65.000 event	
Keypad	10 number key + 6 function key	
Size	140 x 223 x 65 mm	140 x 156 x 50 mm
Display	128 x 64 dots LCD, 3 LED	

ACCESSORIES



SMF-602 READER



SMF-604 READER



BS-603
SERIES PROXIMITY &
SMART CARD READER



BS-20 RELAY BOX



BS-333
ELEVATOR CONTROLLER

